

How to Use Electric Heaters


Heating is electrical so it's important to learn to use it economically to reduce costs whilst also protecting the environment.

BEDROOM HEATERS

Are convector heaters (blow out hot air) with a timer option. Use this timer to control heating and avoid leaving heaters running constantly thus wasting energy.

How to use:

1. Turn on wall switch – power to heater
2. Select 1 of 3 settings.
 - Timed (clock image)
 - Off (0)
 - Manual (hand image) heating is on constant.
3. Timer option
 - To start ensure all pins on timer are pushed in to middle of dial.
 - Then Set the current time – point small arrow to actual time.
 - Pull out the pins for times when you want the heating to start & end, e.g., 7-9am for morning and 4 – 9.00pm for evening heat.
 - This timer option ensures you don't wake up or go to bed cold!




HALL HEATERS – STORAGE HEATER

The storage heaters are very economical to use as they are heated up on the economy night rate and release this heat during the day. How to Use:

- Ensure correct wall switch is turned on and left on. Controls on top of the heater; input/output
- Input knob determines how much heating you are storing up, recommended settings can be viewed close to switch.
- Output determines how much heating you wish to release. Ideally set for 3-4 during the day and increase output when you are home in evenings.

NOTE: this is not instant heat; therefore, the wall switch should not be turned off.



LOUNGE/KITCHEN – 2IN1 CONVECTOR & STORAGE HEATER

2 wall (mains) switches

- establish storage heater switch and leave on constant.
- Establish convector heater switch; (This switch will pump out heat instantly) use this switch for on/off or the off option on heater.

Use storage heating system as above.

Use convector heater to boost heat in room, recommended to switch off when not required.